

C o p 01

WIRING DIAGRAM

SOLDER SIDE		PART SIDE
1P UP	1	1P DOWN
1P LEFT	2	1P RIGHT
1P SHOOT I	3	1P Shoot II
2P UP	4	2P DOWN
2P LEFT	5	2P RIGHT
2P SHOOT I	6	2P Shoot II
COIN 1	7	COIN 2
GND	8	GND
GND	9	GND
+5 VOLT	10	+5 VOLT
+12 VOLT	11	
	12	+12 VOLT
+5 VOLT	13	+5 VOLT
GND	14	GND
GND	15	GND
SELECT-1	16	SELECT-2
	17	SERVICE SW
COUNTER 1	18	COUNTER 2
SPEAKER	19	SPEAKER
	20	RED
GREEN	21	BLUE
GND	22	SYNC

C O B - 0 1 SwitchEinstellung

Dip-Switch I

1 2 3 4 5 6 7 8

off off
off on
on off

off off
off on
on off
on on

off

off
on

off
on

off
on

Coin I

1 Coin 1 Play
1 " 2 "
2 " 1 "

Coin II

1 Coin 3 Play
1 " 6 "
2 " 3 "
3 " 1 "

Demo Sound

an
aus

Monitor normal
Reverse
Tisch
Stand

Dip-Switch II

1 2 3 4 5 6 7 8

off off
off on
on off
on on

off off
off on
on off
on on

off
on

off off
off on
on off
on on

off

Schwierigkeiten

leicht
"
"

schwer

3 Figuren

4 "

5 "

6 "

20.000 Bonus

30.000 "

Zusatzbonus

30.000

50.000

100.000

150.000