

MEXICO 86 OR (KICK N RUN)

29.5.87

WIRING DIAGRAM

SOLDER SIDE		PART SIDE		SOLDER SIDE		PARTS SIDE	
GND	1	GND		GND	1	GND	
GND	2	GND		+5V	2	+5V	
+5V	3	+5V			3		
+5V	4	+5V			4		
-5V	5	-5V			5		
+13V	6	+12V		POST	6	POST	
POST	7	POST			7		
COIN METER B	8	COIN METER A			8		
COIN LOCKOUT B	9	COIN LOCKOUT A			9		
SOUND OUT(-)	10	SOUND OUT (+)		3P UP	10	4P UP	
AUDIO(-)	11	AUDIO(+)		3P DOWN	11	4P DOWN	
GREEN	12	RED		3P LEFT	12	4P LEFT	
SYNC	13	BLUE		3P RIGHT	13	4P RIGHT	
SERVICE SW	14	GND		3P PASS	14	4P PASS	
TILT SW	15	TEST SW		3P SHOT	15	4P SHOT	
COIN SW B	16	COIN SW A			16		
SELECT 2P	17	SELECT 1P			17		
2P RIGHT	18	1P RIGHT		GND	18	GND	
2P UP	19	1P UP					
2P LEFT	20	1P LEFT					
2P DOWN	21	1P DOWN					
2P PASS	22	1P PASS					
2P SHOT	23	1P SHOT					
	24						
	25						
	26						
+5V	27	GND					
+5V	28	GND					

DIP SW A		1	2	3	4	5	6	7	8	
SELECT	OFF	OFF								
SCREEN INVERSION	NORMAL	OFF								
	INVERSION	ON								
TEST MODE	NORMAL	OFF								
	TEST	ON								
ATTRACT SOUND	PRODUCED	OFF								
	NO PRODUCED	ON								
COIN A	1COIN 1PLAY					OFF	OFF			
	1COIN 2PLAYS					ON	OFF			
	1COIN 3PLAY					OFF	ON			
	1COIN 4PLAYS					ON	ON			
COIN B	1COIN 1PLAY							OFF	OFF	
	1COIN 2PLAYS							ON	OFF	
	1COIN 3PLAY							OFF	ON	
	1COIN 4PLAYS							ON	ON	

DIP SW B		1	2	3	4	5	6	7	8	
DIFFICULTY										
EASY(A)-DIFFICULT(D)	B	OFF	OFF							
	A	ON	OFF							
	C	OFF	ON							
	D	ON	ON							
PK-MATCHES										
	2 PER TEAK					OFF				
	4 PER TEAK					ON				
SELECT	OFF					OFF				
NUMVER MATCHES										
	5 TEAK							OFF		
	2 TEAK							ON		
SELECT	ON							ON		
	4COIN 4PLAY							ON		