COREO CORPORATION

Dae Yang B/D 204, 5-27 Shin Kong Duck-Dong Mapo-Ku Seoul, Korea.

TEL: (02) 703-5277/8. FAX: (02) 704-1781

THE LASTDAY

WIRING DIAGRAM

Technical information	SOLDER SIDE		·	COMPONENT CT'DE			
 1 Required Power Capacity +5V 4A or more +12V 1A' or more (2) Output * R - analog, positive G - analog, positive B - analog, positive SYNC - H-V complexed, negative Play Instruction Control your jet fighter by using the 8-way joystick SHOOT 1 MACHINE GUN SHOOT 2 FIRE BOMB B Available one more FIRE BOMB P Power up Machine gun Available 1UP bonus 	SOLDER SIDE GND GND +5V +5V -5V +12V COIN COUNTER2 SP(-) VIDEO GREEN VIDEO GREEN VIDEO SYNC SERVICE SW COIN SW 2 START SW 2 2P DOWN 2P LEFT 2P RIGHT 2P SHOOT 1 2P SHOOT 2	ABCDEFHJKLMNPRSHUVWXYN ab c	1 2 3 4 5 6 7 8 9 10 11 2 13 4 15 16 6 7 8 9 20 1 2 2 2 3 2 4 2 5	VIDEO RED VIDEO BLUE VIDEO GND COIN SW 1 START SW 1 1P UP 1P DOWN 1P LEFT			
on getting all of four parts of jet fighter.	GND GND	d e ť	26 27 28	GND- GND			
CONTROL PANEL			NUO 	TER			
8-WAY LEVER BUTTON 1 BUTTON2							

THE LASTDAY DIP SW

-

* DIP SW A

SETTING	POSITION	1	2	3	4	5	6	1	8
TEST MODE	* NORMAL GAME TEST MODE	OFF							
COIN TYPE '	* TYPE 1 TYPE 2		OFF		•				
DEMO SOUND	* SOUND NO SOUND			OFF ON	•				
SCREEN .	* NORMAL INVERSEION				OFF			•	
	· TYPE 1	TYPE2						:	
PLAY PRICING COIN 1	* 1 COIN 1 PLAY 1 COIN 2 PLAY 2 COIN 1 PLAY 2 COIN 3 PLAY	2 0	COIN COIN COIN COIN	1 P 1 P 1 P 1 P	LAY	OFF ON OFF ON	OFF OFF ON ON	(Sec.	
COIN 2	* 1 COIN 1 PLAY 1 COIN 2 PLAY 2 COIN 1 PLAY 2 COIN 3 PLAY		COIN COIN COIN COIN	3 P 4 P	LAY LAY LAY LAY			OFF ON OFF ON	OFF OFF ON ON

* DIP SW B *

•

14

5

SETTING	POSITION	1	2	3	4	5	6.	7	8
NUMBER OF PLAYER	* 3 2 4 1	OFF ON OFF ON	OFF OFF ON ON						
GAME DIFFICULTY	* NORMAL EASY HARD HARDEST			OFF ON OFF ON	OFF OFF ON ON				•,
1 UP BONUS	* 200,000 EVERY 240,000 EVERY 280,000 ONLY NO BONUS					OFF ON OFF ON	OFF OFF ON ON		
HERO'S SPEED	* HIGH LOW							OFF	
CONTINUED PLAY	* WITH WJTHOUT			2					OFF