

S.S-MISSION

© 1992 COMAD INDUSTRY CO., LTD. ALL RIGHTS RESERVED.

...Operator's Manual...

■ PIN ASSIGNMENT

■ DIP SWITCH SETTINGS

DIP SWITCH 1

SOLDER SIDE		COMPONENT SIDE
GROUND	1	GROUND
GROUND	2	GROUND
+ 5V	3	+ 5V
+ 5V	4	+ 5V
+ 12V	6	+ 12V
KEY	7	KEY
COIN COUNTER 2	8	COIN COUNTER 1
	9	
SPEAKER (-)	10	SPEAKER (+)
	11	
VIDEO GREEN	12	VIDEO RED
VIDEO SYNC	13	VIDEO BLUE
SERVICE SW	14	VIDEO GROUND
	15	
COIN SW 2	16	COIN SW 1
2P START	17	1P START
2P UP	18	1P UP
2P DOWN	19	1P DOWN
2P LEFT	20	1P LEFT
2P RIGHT	21	1P RIGHT
2P SHOOTING	22	1P SHOOTING
2P BOMB	23	1P BOMB
	24	
	25	
GROUND	26	GROUND
GROUND	27	GROUND
	28	GROUND

DIP SWITCH 1

ITEM	DESCRIPTION	1	2	3	4	5	6	7	8
PLAYER COUNTS	3	OFF	OFF						
	2	ON	OFF						
	4	OFF	ON						
	1	ON	ON						
DIFFICULTY	NORMAL					OFF	OFF		
	EASY					ON	ON		
	DIFFICULT					OFF	ON		
	MORE DIFFICULT					ON	ON		
SCREEN F/F	NO								OFF
	YES								ON
DEFAULT SETTING		OFF	OFF	OFF	OFF	OFF	OFF	OFF	OFF

DIP SWITCH 2

ITEM	DESCRIPTION	1	2	3	4	5	6	7	8
COIN SW 1	1 COIN 1 CREDIT	OFF	OFF	OFF					
	2 COIN 1 CREDIT	ON	OFF	OFF					
	3 COIN 1 CREDIT	OFF	ON	OFF					
	4 COIN 1 CREDIT	ON	ON	OFF					
	1 COIN 2 CREDIT	OFF	OFF	ON					
	1 COIN 3 CREDIT	ON	OFF	ON					
	1 COIN 4 CREDIT	OFF	ON	ON					
	FREE PLAY	ON	ON	ON					
COIN SW 2	1 COIN 1 CREDIT				OFF	OFF	OFF		
	2 COIN 1 CREDIT				ON	OFF	OFF		
	3 COIN 1 CREDIT				OFF	ON	OFF		
	4 COIN 1 CREDIT				ON	ON	OFF		
	1 COIN 2 CREDIT				OFF	OFF	ON		
	1 COIN 3 CREDIT				ON	OFF	ON		
	1 COIN 4 CREDIT				OFF	ON	ON		
	FREE PLAY				ON	ON	ON		
DEMONSTRATION SOUND	YES								OFF
	NO								ON
DEFAULT SETTING		OFF	OFF	OFF	OFF	OFF	OFF	OFF	OFF

1992 COMAD INDUSTRY CO., LTD. ALL RIGHTS RESERVED.