

BREYWOOD

Wiring Diagram

Solder side

Component    Side

GND	!	GND
GND	2	GND
+ 5V	3	+5V
+5V	4	+5V
	5	
+12V	6	+12V
	7	
COIN 2	8	COIN 1
	9	
SPEAKER(-)	10	SPEAKER (+)
	11	
GREEN	12	RED
SYNC	13	BLUE
SERVICE SW	14	GND
	15	
COIN SW 2	16	COIN SW1
START SW 2	17	START SW 1
2P UP	18	1P UP
2P DOWN	19	1 P DOWN
2P LEFT	20	1P LEFT
2P RIGHT	21	1P RIGHT
2P PUSH 1	22	1P PUSH 1
2P PUSH 2	23	1P PUSH 2
	24	
	25	
	26	
GND	27	GND
GND	28	GND

Dips witch 1

1    2    3    4    5    6    7    8

SREEN NORMAL

OFF

INVERSE

ON

NOT USING

OFF OFF OFF OFF OFF OFF OFF OFF

SCREEN STOP

NO

OFF

YES

ON

DIPS SWITCH 2		1	2	3	4	5	6	7	8
<u>POWER</u>	1000	OFF	OFF	OFF	OFF				
	200	OFF	OFF	OFF	ON				
	300	OFF	OFF	ON	OFF				
		OFF	OFF	ON	ON				
	500	OFF	ON	OFF	OFF				
	600	OFF	ON	OFF	ON				
	700	OFF	ON	ON	OFF				
	800	OFF	ON	ON	ON				
	900	ON	OFF	OFF	OFF				
	2000	ON	OFF	OFF	ON				
	3000	ON	OFF	ON	OFF				
	4000	ON	OFF	ON	ON				
	5000	ON	ON	OFF	OFF				
	6000	ON	ON	OFF	ON				
	7000	ON	ON	ON	OFF				
	8000	ON	ON	ON	ON				
GAME DIFFICULTY									
	NORMAL					OFF	OFF		
	1					ON	OFF		
	2					OFF	ON		
	3					ON	ON		
	NOT USING							OFF	
	DEMO SOUND								
	NO								OFF
	YES								ON

OFF  
ON

NO  
YES