

42 GAMES

JAMMA

Solder Side	No.	No.	Part Side
GND	A	1	GND
GND	B	2	GND..
+5V	C	3	+5V
+5V	D	4	+5V
	E	5	
+12V	F	6	+12V
	H	7	
	J	8	
	K	9	
SPEAKER -	L	10	SPEAKER +
	M	11	
GREEN	N	12	RED
SYNC	P	13	BLUE
	R	14	
	S	15	
	T	16	COIN SW
2P START	U	17	1P START
2P UP	V	18	1P UP
2P DOWN	W	19	1P DOWN
2P LEFT	X	20	1P LEFT
2P RIGHT	Y	21	1P RIGHT
2P SW1	Z	22	1P SW1
2P SW2	a	23	1P SW2
2P SW3	b	24	1P SW3
	c	25	
	d	26	
GND	e	27	GND
GND	f	28	GND

Auswahl rückgängig machen
Level/Spiel auswählen
Auswahl 1/2 Spieler

DIP-SW

	1	2	3	4	5	6	7	8	9	10
1 Münze/1 Kredit		OFF								OFF
1 Münze/2 Kredite		ON								OFF
2 Münzen/2 Kredite		OFF								ON
3 Münzen/1 Kredit		ON								ON
Time: 60 Min.						OFF	OFF	OFF		
5 Min.						OFF	OFF	ON		
7 Min.						OFF	ON	OFF		
10 Min.						OFF	ON	ON		
15 Min.						ON	OFF	OFF		
20 Min.						ON	OFF	ON		
25 Min.						ON	ON	OFF		
30 Min.						ON	ON	ON		
Ohne Funktion:	OFF	OFF	OFF	OFF	OFF				OFF	