TRANSFORMER (ASTRO FLASH)

1 1 1 2	COIN COIN COIN COIN COIN	1 2 3 4 5	CREDITS CREDITS CREDITS	OFF ON OFF	OFF	OFF	Section 2	CONTRACTOR OF THE PERSON	DECEMBER 1888	th copyrigates	and the same of
1 1 1 2	COIN COIN COIN	3	CREDITS				OFF	OFF	OFF	OFF	OFF
1 2	COIN COIN COIN	4		OFF	OFF	OFF	OFF	ON	OFF	OFF	OFF
1 2	COIN		CREDITE	OFF	ON	OFF	OFF	OFF	ON	OFF	OFF
1 2	COIN	5	CULDI13	ON	ON	OFF	OFF	ON	ON	OFF	OFF
			CREDITS	OFF	OFF	ON	OFF	OFF	OFF	ON	OFF
		8	CREDITS	ON	OFF	ON	OFF	ON	OFF	ON	OFF
	COINS	1	CREDIT	OFF	ON	ON	OFF	OFF	ON	ON	OFF
. 3	COINS	1	CREDIT	ON	ON	ON	OFF	ON	ON	ON	OFF
4	COINS	1	CREDIT	OFF	OFF	OFF	ON	OFF	OFF	OFF	ON
2	COINS	3	CREDITS	ON	OFF	OFF	ON	ON	OFF	OFF	ON
2	COINS	1	CREDIT	40.000				11201			
	COINS	2	CREDITS	OFF	ON	OFF	ON	OFF	ON	OFF	ON
5	COINS	3	CREDITS	OFF							
6	COINS	4	CREDITS								150
2	COINS	1	CREDIT		ON	OFF	ON	25.0			
4	COINS	3	CREDITS	ON	UN	UFF	ON	ON	ON	OFF	ON
1	COIN .	1	CREDIT		Constitution in the						
2	COINS	2	CREDITS	1				7/_			
3	COINS	3	CREDITS	OFF	OFF	ON	ON	OFF	OFF	ON	ON
4	COINS	4	CREDITS		-					100	
5	COINS	6	CREDITS								
1	COIN	1	CREDIT	100000000000000000000000000000000000000	THE POWER		-				-
2	COINS	2	CREDITS					-24			
3	COINS	3	CREDITS	ON	OFF	ON	ON	ON	OFF	ON	ON
4	COINS	. 5	CREDITS	1						100	
1	COIN	1	CREDIT							-	
2	COINS	3	CREDITS	OFF	ON	OH	ON ON	OFF	ON	ON	ON
1	COIN	1	CREDIT	ON	ON	ON	ON	ON	ON	ON	ON

	GAME	OPTION	SETTING
--	------	--------	---------

- 1 or 2P

OPTI	ON	1	2	3	4	5	6	7	8
ADVERTISE SOUND	OFF ON		OFF ON						
NUMBER OF PLAYER	3 . 4 5 FREE			OFF ON OFF	OFF				
EXTRA PLAYER	NORMAL EASY HARD					ON OFF			
GAME	NORMAL EASY					ON	ON	ON	OFF
DIFFICULTY	HARDEST	OFF				1 - 4		OFF	ON

DIP SW #2

SOLDER SIDE		PARTS SIDE
	1	
COIN 2	2	COIN 1
SERVICE	3	TEST
	4	
2P START	5	1P START
DOWN	6	UP
LEFT	7	RIGHT
SHOOT 2	8	SHOOT 1
	9	
	10	
	11	
	12	
	13	
GREEN	14	RED
SYNC	15	BLUE
	16	
	17	
	18	GND
	19	COIN COUNTER
	20	
	21	
	22	
	23	+5V
1101	24	GND
+12V	$\sqrt{\frac{25}{36}}$	+12V
	VL26	CND;

27 SPEAKER

SPEAKER