

WIRING DIAGRAM

SOLDER SIDE		PARTS SIDE
GND	1	GND
GND	2	GND
+5V	3	+5V
+5V	4	+5V
N.C	5	N.C
+12V	6	+12V
	7	
	8	
	9	
SP(-)	10	SP(+)
N.C	11	N.C
GREEN	12	VIDEO RED
SYNC	13	VIDEO BLUE
SERVICE SW	14	GND
N.C	15	N.C
COIN SW 2	16	COIN SW 1
START SW 2	17	START SW 1
2P UP	18	1P UP
2P DOWN	19	1P DOWN
2P LEFT	20	1P LEFT
2P RIGHT	21	1P RIGHT
2P PUSH 1	22	1P PUSH 1
2P PUSH 2	23	1P PUSH 2
N.C	24	N.C
N.C	25	N.C
N.C	26	N.C
GND	27	GND
GND	28	GND

DIP SW 2

	1	2	3	4	5	6	7	8
PLAYER	OFF	OFF						
	ON	OFF						
	OFF	ON						
	ON	ON						
GAME LEVEL								
	LEVEL 1 EASY					OFF	OFF	OFF
	LEVEL 2 EASY					ON	OFF	OFF
	LEVEL 3 EASY					OFF	ON	OFF
	LEVEL 4 EASY					ON	ON	OFF
	LEVEL 5 NOMAL					OFF	OFF	ON
	LEVEL 6 EASY					ON	OFF	ON
	LEVEL 7 EASY					OFF	ON	ON
	LEVEL 8 DIFFCULY					ON	ON	ON
MEMO SOUND	ON							OFF
	OFF							ON
CONTINUE GAME	ENABLE							OFF
	DISABLE							ON
GAME STYLE	TITLE							OFF
	UPRIGHT							ON

DIP SW 1

	1	2	3	4	5	6	7	8
COIN A	1COIN/1CREDIT	OFF	OFF	OFF				
	1COIN/2CREDIT	ON	OFF	OFF				
	1COIN/3CREDIT	OFF	ON	OFF				
	1COIN/4CREDIT	ON	ON	OFF				
	1COIN/5CREDIT	OFF	OFF	ON				
	2COIN/1CREDIT	ON	OFF	ON				
	3COIN/1CREDIT	OFF	ON	ON				
	4COIN/1CREDIT	ON	ON	ON				
COIN B	1COIN/1CREDIT			OFF	OFF	OFF		
	1COIN/2CREDIT			ON	OFF	OFF		
	1COIN/3CREDIT			OFF	ON	OFF		
	1COIN/4CREDIT			ON	ON	OFF		
	1COIN/5CREDIT			OFF	OFF	ON		
	2COIN/1CREDIT			ON	OFF	ON		
	3COIN/1CREDIT			OFF	ON	ON		
	4COIN/1CREDIT			ON	ON	ON		
SCREEN INVERSION								OFF
TEST MODE	NOMAL							OFF
	TEST							ON