

(Stranoid)
BLOCK II
WIRING DIAGRAM

86/12/15

COMPONENT	SIDE	SOLDER	SIDE
GND	1	GND	
GND	2	GND	
GND	3	GND	
+5V	4	+5V	
+5V	5	+5V	
+12V	6	+12V	
+12V	7	+12V	
RED	8		
GREEN	9	BLUE	
SYNC	10		
	11	SPEAKER	
	12		
	13		
	14		
	15	COIN	
2P START	16	1P START	
	17		
	18		
2P RIGHT	19	1P LEFT	
2P LEFT	20	1P RIGHT	
2P FIRE	21	1P FIRE	
	22		

DIP SW 1		1	2	3	4	5	6	7	8
UPRIGHT	TABLE TYPE	OFF							
	STANDARD	ON							
PLAYER'S NUMBER	3			OFF					
	5			ON					
BONUS	30K..60K				OFF				
	20K ONLY				ON				
DIFFICULTY	EASY					OFF			
	HARD					ON			
TEST MODE	NORMAL						OFF		
	TEST						ON		
SCREEN	NORMAL							OFF	
	INVERSE							ON	

FREE HARNESS ASSY NO.	COLORS	SIGNALS
1.	YELLOW	LEFT
2	BLACK	+5V
3	RED	GND
4	BLUE	RIGHT

