

Karate Champ II

46

Monitor V

Vier 4-Wege - Hebel.

HARNESS CONNECTION

1) Terminal Numbering CR7E-44DA-3.96E (HIROSE) 3.96mm Pitch

1 2 3 4 5 6 7 8 9 10 11 12 13 14 15 16 17 18 19 20 21 22



B C D E F H J K L M N P R S T U V W X Y Z



2) Signals to Terminal

Connector CN2 CR7E-44DA-3.96E

Brücke, Seite

Leitseite

Pin No.	Signal	Pin No.	Signal
1	1P RIGHT DOWN	A	2P RIGHT DOWN
2	1P RIGHT UP	B	2P RIGHT UP
3	1P RIGHT LEFT	C	2P RIGHT LEFT
4	1P RIGHT RIGHT	D	2P RIGHT RIGHT
5	1P LEFT DOWN	E	2P LEFT DOWN
6	1P LEFT UP	F	2P LEFT UP
7	1P LEFT LEFT	H	2P LEFT LEFT
8	1P LEFT RIGHT	J	2P LEFT RIGHT
9		K	
10		L	
11	1P SELECT	M	3P SELECT
12	COIN 1	N	COIN 2
13	COIN COUNTER 1	P	COIN COUNTER 2
14	TV. B	R	TV. G
15	SYNC	S	TV. R
16		T	
17	SOUND +	U	SOUND -
18	+12V	V	<i>-5</i>
19	+5V	W	+5V
20	+5V	X	+5V
21	CRT GND	Y	GND
22	GND	Z	GND

*auf
Player*