

KONG III

<u>PARTS/F</u>	<u>SOLDER/F</u>
GND	: 1 : GND
GND	: 2 : GND
+ 5	: 3 : + 5
+ 5	: 4 : + 5
+12	: 5 : +12
- 5	: 6 : - 5
	: 7 : COIN
2P SELECT	: 8 : 1P SELECT
2P RIGHT	: 9 : 1P RIGHT
2P LEFT	: 10 : 1P LEFT
2P UP	: 11 : 1P UP
2P DOWN	: 12 : 1P DOWN
2P JUMP	: 13 : 1P JUMP
	: 14 :
	: 15 : SERVICE /Coin
GND	: 16 : GND
TV-G	: 17 : TV-R
TV-SYNC	: 18 : TV-B
AUDIO OUT	: 19 :
(+24)	: 20 : (COUNTER)
GND	: 21 : GND
GND	: 22 : GND

Number of JUNIOR	Condition of CPU SW							
	A	B	C	D	E	F	G	H
3	OFF	OFF						
4	ON	OFF						
5	OFF	ON						
6	ON	ON						
Extra score								
10000 Points			OFF	OFF				
15000 "			ON	OFF				
20000 "			OFF	ON				
25000 "			ON	ON				
Game Charge								
1 coin 1 credit					OFF	OFF	OFF	
1 " 2 "					OFF	ON	OFF	
1 " 3 "					OFF	OFF	ON	
1 " 4 "					OFF	ON	ON	
2 " 1 "					ON	OFF	OFF	
3 " 1 "					ON	ON	OFF	
4 " 1 "					ON	OFF	ON	
5 " 1 "					ON	ON	ON	
Table Type								OFF
Upright								ON

- : 1 : -5 V
- : 2 : -5 V
- : 3 : -5 V
- : 4 : -5 V
- : 5 : GND
- : 6 : GND
- : 7 : GND
- : 8 : GND
- : 9 : +5 V
- :10 : +5 V

VIDEO BOARD SIDE CONNECTOR (P4)