

Mustache Boy

Mustache Boy

Boy



GND	1	GND
GND	2	GND
+5V	3	+5V
+5V	4	+5V
-5V	5	-5V
+12V	6	+12V
	7	
COIN COUNTER 2	8	COIN COUNTER 1
	9	
SPEAKER (-)	10	SPEAKER (+)
	11	
VIDEO GREEN	12	VIDEO RED
VIDEO SYNC	13	VIDEO BLUE
	14	VIDEO GND
	15	
COIN SW 2	16	COIN SW 1
COIN SW 2	17	START SW. 1
2P CONTROL UP	18	1P CONTROL UP
2P DOWN	19	1P DOWN
2P LEFT	20	1P LEFT
2P RIGHT	21	1P RIGHT
2P PUSH1	22	1P PUSH1
2P PUSH2	23	1P PUSH2
	24	
	25	
	26	
GND	27	GND
GND	28	GND

DIPSW 1		1	2	3	4	5	6	7	8
COIN1 COIN/CREDIT	1/1	OFF	OFF	OFF					
	2/1	ON	OFF	OFF					
	1/3	OFF	ON	OFF					
	4/1	ON	ON	OFF					
	1/2	OFF	OFF	ON					
	3/1	ON	OFF	ON					
	1/5	OFF	ON	ON					
	5/1	ON	ON	ON					
COIN2 COIN/CREDIT	1/1				OFF	OFF			
	2/1				ON	OFF			
	1/2				OFF	ON			
	2/2				ON	ON			
TEST MODE	NORMAL						OFF		
	TEST						ON		
FREE PLAY								OFF	
								ON	
SCREEN REVERSED (WARD SW)									OFF
									ON
SETTING AT THE TIME OF		OFF	OFF	OFF	OFF	OFF	OFF	OFF	OFF

DIPSW 2		1	2	3	4	5	6	7	8
GAME STYLE	UPLIGHT	OFF							
	TABLE	ON							
DIFFICULTY	0		OFF	OFF					
	1		ON	OFF					
	2		OFF	ON					
	3		ON	ON					
NUMBER OF PLAYERS	3				OFF	OFF			
	1				ON	OFF			
	4				OFF	ON			
	5				ON	ON			
DEMO SOUND							OFF		
							ON		
SETTING AT THE TIME OF		OFF	ON	OFF	OFF	OFF	OFF	OFF	OFF

M U S T A C H E B O Y

<u>Solder Side</u>		<u>Parts Side</u>	
GND	1	GND	
GND	2	GND	
+5V	3	+5V	
+5V	4	+5V	
-5V	5	-5V	
+12V	6	+12V	
	7		
COIN COUNTER 2	8	COIN COUNTER 1	
	9		
SPEAKER(-)	10	SPEAKER(+)	
	11		
VIDEO GREEN	12	VIDEO RED	
VIDEO SYNC	13	VIDEO BLUE	
	14	VIDEO GND	
	15		
COIN SWITCH 2	16	COIN SWITCH 1	
START SWITCH 2	17	START SWITCH 1	
2P CONTROL UP	18	1P CONTROL UP	
2P CONTROL DOWN	19	1P CONTROL DOWN	
2P CONTROL LEFT	20	1P CONTROL LEFT	
2P CONTROL RIGHT	21	1P CONTROL RIGHT	
2P CONTROL PUSH 1	22	1P CONTROL PUSH 1	
2P CONTROL PUSH 2	23	1P CONTROL PUSH 2	
	24		
	25		
	26		
GND	27	GND	
GND	28	GND	

		1	2	3	4	5	6	7	8
DIP SW 1									
COIN 1 (COIN/CREDIT)									
	1/1	OFF	OFF	OFF					
	2/1	ON	OFF	OFF					
	1/3	OFF	ON	OFF					
	4/1	ON	ON	OFF					
	1/2	OFF	OFF	ON					
	3/1	ON	OFF	ON					
	1/5	OFF	ON	ON					
	5/1	ON	ON	ON					
COIN 2 (COIN/CREDIT)									
	1/1				OFF	OFF			
	2/1				ON	OFF			
	1/2				OFF	ON			
	2/3				ON	ON			
TEST MODE (NORMAL)								OFF	
" (TEST)								ON	
FREE PLAY									ON
NORMAL PLAY									OFF
SCREEN REVERSE (HARD SW)									ON
NORMAL SCREEN									OFF
DIP SW 2									
UPLIGHT TYPE		1	2	3	4	5	6	7	8
TABLE TYPE		OFF							
DIFFICULTY 0		ON							
1			OFF	OFF					
2			ON	OFF					
3			OFF	ON					
NUMBER OF PLAYER			ON	ON					
3					OFF	OFF			
1					ON	OFF			
2					OFF	ON			
4					ON	ON			
DEMO SOUND								ON	
NO DEMO SOUND								OFF	

* It is not used that any terminal does not write down. The other terminal (especially -5V) must be connected certainly.

* 3 is most difficult.

* At first the beginning, bonus point is 50000 point.

DOMINATOR