

UNTOUCHABLE DIP-SW SPAC

DIP-SW. 1

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8
SELECTOR OF STAGE 4 STAGE 3 STAGE	OFF ON							
SCORE LIMIT SELECTOR 200. 1000. 10000. 70000 250. 2000. 10000. 70000 500. 5000. 10000. 70000 1000. 5000. 10000. 70000			OFF OFF OFF O N O N OFF O N O N					
MAIN GAME DIFFICULTY NOMAL 2 EASY 1 3 DIFFICULT 4				off OFF OFF O N O N OFF O N O N				
STAGE UP DIFFICULTY NOMAL 2 EASY 1 3 DIFFICULT 4						OFF OFF OFF O N O N O N O N O N		
W-UP DIFFICULTY NOMAL DOFFICULT								OFF O N

DIP-SW. 2

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8
DEMO SOUND CUT	O N							
VOICE CUT		O N						
AUMIT CUT			O N					
AUTO HOLD CUT				O N				
COIN 2 1 COIN 5 CREDIT 8 CREDIT					OFF O N			
COIN 1 SCORE 1 CREDIT 25 SCORE CREDIT 5 SCORE " 10 " " 15 " " 20 " " 50 " " 75 " " 100 "						OFF OFF OFF OFF OFF O N OFF O N OFF OFF O N O N O N OFF OFF O N OFF O N O N O N OFF O N O N O N		

36 PIN TYPE

B SOIDER SIDE	A	PART SIDE
COM P1	1	COM P2
COM P3	2	COM P4
COM P5	3	
	4	
	5	GND
COIN 2 SW	6	MEMORY RESET
ANALIZDR	7	TEST SW
R	8	G
B	9	SYNC
SPEAKER	10	SPEAKER
1P 9	11	2P 9
1P 8	12	2P 8
1P 5	13	2P 5
1P 4	14	2P 4
1P 2	15	2P 2
1P 1	16	2P 3
	17	COIN 1 SW
	18	SERVICE SW

20PIN

GND	1	GND
GND	2	GND
+5V	3	+5v
+5V	4	+5v
+12V	5	
	6	+12V
+5V	7	+5V
+5V	8	+5V
GND	9	GND
GND	10	GND

56PIN TYPE

B SOIDER SIDE	A	PART SIDE
COM P1	1	COM P2
COM P3	2	COM P4
COM P5	3	
	4	
GND	5	GND
COIN 2 SW	6	MEMORY RESET
ANALIZER	7	TEST SW
R	8	G
B	9	SYNC
SPEAKER	10	SPEAKER
1P 9	11	2P 9
1P 8	12	2P 8
1P 5	13	2P 5
1P 4	14	2P 4
1P 2	15	2P 2
1P 1	16	2P 3
	17	COIN 1 SW
	18	SERVICE SW
GND	19	GND
GND	20	GND
+5V	21	+5V
+5V	22	+5V
+12V	23	+12V
	24	
+5V	25	+5V
+5V	26	+5V
GND	27	GND
GND	28	GND



